

Tricks and secret tips for Motorola cellphone

Free Motorola mobile tips, tricks, and secrets:- All the tips and tricks provided by unique Tricks are free and it's not necessary to sign up also.

Free call tip

1 Enter the phone number

2 Enter OK

3 Type *#06#

4 Press Button C

5 and finally press the button for power off.

You should now be able to talk without being billed.

To check Motorola mobile or cell phones IMEI (International Mobile Equipment Identity) On the main screen type *#06# Information you get from the IMEI (International Mobile Equipment Identity) XXXXXX XX XXXXXX X FAC SNR SP TAC = Type approval code of your Motorola Mobile FAC = Final assembly code of your cell phone SNR = Serial number of your Motorola Phone SP = Spare Other secret tricks for Motorola mobile or cell phone Code to lock keys. Press together *7 Note: [] (pause) means the * key held in until box appears. Select phone line - (use this to write things below the provider name): [] [] 0 0 8 [] 1 [] Add phonebook to main menu: [] [] 1 0 5 [] 1 [] Add messages to main menu: [] [] 1 0 7 [] 1 [] Copy SIM memory (phonebook menu): [] [] 1 0 8 [] 1 [] Eng Field options (main menu): [] [] 1 1 3 [] 1 [] Slow (Frequency of search menu): [] [] 1 0 1 [] 1 [] Medium (Frequency of search menu): [] [] 1 0 2 [] 1 [] Fast (Frequency of search menu): [] [] 1 0 3 [] 1 [] Enable EFR: [] [] 1 1 9 [] 1 [] Function: [] [] # # # [] 1 [] Change pin: [] [] 0 0 4 [] 1 [] Unblocking using the "puk" number: [] [] 0 0 5 [] 1 []

You can change GSM frequencies to 900/1800 by entering the engineering model. Following the below steps: Enter menu and press 048263* quickly, Then you will enter the secret engineering menu under "Opcode" Input 10*0*3 for GSM 900 10*0*4 for GSM 1800 10*0*5 for GSM 1900 10*0*6 for dual band GSM 900/1800 10*0*7 for dual band GSM 850/1900 To add extra message space 4 your Motorola C350 C450 C550 or C650, Press menu button, press 048263* quickly, then on the popup menu enter 47 press ok. Press 50 and ok. Press 1 ok. Press 64 ok. Press 1 ok. Press 186 and ok. You will receive an extra 50 message memory space. Switch phone off and back on. View our Mobile tips and Guidelines for better Handling of Mobile phone. SECRET PRANK Change closed caller group (settings >security settings>user groups) to 00000 and your phone will sound the message tone when you are near a radar speed trap. Setting it to 500 will cause your phone 2 set off security alarms at shop exits. Try this secret trick if you can handle the unexpected. Note: This secret trick wont work with all phones Models. THE DETECTIVE TRICK (Mobile Spying) Now you can spy on anyone using your cell phone. Just do the following. 1. Activate the "Automatic Answer" in the headset profile of your cell phone and set the ringing volume to "Mute" 2. Short-circuit the left middle and right pins on the bottom of the mobile phone with all connections touching each other this will activate profile "Headset". If you can't do this just keep your earphone connected to mobile. 3. Now place it under a table in a room and call it. Now you can use your phone for checking out what people are talking about in a room. Just call on your phone. 4. The phone receives the call without ringing and you can listen to what people are saying. Motorola V3688

*#06# for checking the IMEI (International Mobile Equipment Identity)

Enhanced Full Rate Codec (EFR):

To Enable EFR press [] [] [] 119 [] 1 [] OK.

To Disable EFR press [] [] [] 119 [] 0 [] OK

NOTE: Nothing appears on Screen.

Other Phones from Motorola (CD 160, CD 520, 920, 930)

Motorola CD 160

Press menu and type one of these numbers and press OK:

11 = Status Review

13 = Available Networks

14 = Preferred Networks

22 = Select Keypad Tones

25 = Require SIM Card PIN

26 = Language Selection

32 = Repetitive Timer

33 = Single Alert Timer

- 34 = Set IN-Call Display
- 35 = Show Call Timers
- 36 = Show Call Charges
- 37 = Call Charge Settings
- 38 = Reset All Timers
- 43 = Reset All Timers
- 45 = Show Last Call
- 46 = Total For All Calls
- 47 = Lifetime Timer
- 51 = Change Unlock Code
- 52 = Master Reset
- 53 = Master Clear (Warning!! May result in deleting the Message Editor!!!)
- 54 = New Security Code
- 55 = Automatic Lock
- 63 = Battery Saving Mode

Free call tip

- 1 Enter the phone number
- 2 Enter OK
- 3 Type *#06#
- 4 Press Button C
- 5 and finally press the button for power off.

You should now be able to talk without being billed.

Type 1#, 2#.....54# on the keypad (when you're not in the menu) to get the phone number used for with this key when speed dialing.

Keyboard lock

if you push * and # on the same time your keyboard locked. When you press it again, you unlock your keyboard.